

VEHICLE

Connect and run a wire from +12VDC of reverse light to pin #2 in vehicles trailer plug.

Reverse light

Trailer plug

Camera trailer plug

Connect to CAM 2 input from screen

Connect green wire to CAM 2 Trigger from screen

trailer plug

Connect green wire from camera plug to Pin #2 in trailer plug

Camera trailer plug

TRAILER

Connect to trailer camera

1. Check to see if vehicle trailer plug has been fitted with a reverse wire. If not run a wire from the +12VDC to the vehicles trailer plug and connect to PIN #2.
2. Mount trailer plugs to vehicle and trailer.
3. On each camera trailer plug there is a green trigger wire. For the plug on the trailer, the green wire needs to be run into the Standard trailer plug onto PIN #2. **Note: check the trailer harness going between the vehicle and trailer and check if it includes the reverse wire fitted between the two sockets. If it is not fitted you will need to add this wire.**
4. Now go to the Camera trailer plug mounted onto the vehicle. Connect black plug to CAM2 input and connect Green wire to CAM 2 trigger from screen.
5. Once intallation is complete go into the screen settings and set camera Priority to CAM2. So when trailer is attached to vehicle the camera on trailer will be priority and dispay when vehicle is in reverse.